Motion detector - Professional Line

sensIQ S

EVO black EAN 4007841 034979 Article number 034979








Function description

The evolution of perfection. The sensIQ S is just as perfect as its larger role model. For indoors and outdoors, ideal for building entrances, loading bays, for mounting heights of up to 5 m, quadruple sensor system for optimum surveillance over 3x100° coverage angle, 20 m reach (tangential), reach setting to the accuracy of a metre in 3 independent directions. Remote control and corner wall mount bracket included.

Technical specifications

| Dimensions (L x W x H) | 128 x 114 x 74 mm | LED lamps > 8 W |
|----------------------------|--|--|
| With motion detector | Yes | Capacitive load in μF |
| Manufacturer's Warranty | 5 years | Power supply, detail |
| Settings via | Remote control, Potentiometers, Smart Remote | Sensor Technology |
| | | Mounting height |
| With remote control | Yes | Mounting height max. |
| Version | black | Optimum mounting height |
| PU1, EAN | 4007841034979 | Detection angle |
| Туре | Motion detectors | Angle of aperture |
| Application, place | Indoors, Outdoors | Sneak-by guard |
| Application, room | multi-storey / underground car park, outdoors, warehouse, front door, all round the building, courtyard & driveway, Indoors | Capability of masking out indivi segments |
| | | Electronic scalability |
| Colour | black | Mechanical scalability |
| Colour, RAL | 9005 | Reach, radial |
| Includes corner wall mount | Yes | Reach, tangential |
| Installation site | wall, corner | Switching zones |



600 W

10.2022 Page 1 from 3

Motion detector - Professional Line

sensIQ S

EVO black EAN 4007841 034979 Article number 034979



Technical specifications

| Installation | Surface wiring, Wall, corner | |
|--|------------------------------|--|
| IP-rating | IP54 | |
| Ambient temperature | -20 – 50 °C | |
| Material | Plastic | |
| Mains power supply | 100 – 240 V / 50 – 60 Hz | |
| Switching output 1, resistive | 2000 W | |
| Fluorescent lamps, electronic ballast1500 W | | |
| Fluorescent lamps, uncorrected | 1000 VA | |
| Fluorescent lamps, series-corrected | d 700 VA | |
| Fluorescent lamps, parallel- corrected | 1000 VA | |
| Switching output 1, low-voltage halogen lamps | 1000 VA | |
| LED lamps < 2 W | 100 W | |
| LED lamps > 2 W < 8 W | 300 W | |

| Functions | Normal / test mode, Manual ON / ON-OFF |
|----------------------------|---|
| Twilight setting | 2 – 1000 lx |
| Time setting | 5 s – 15 Min. |
| Basic light level function | No |
| Main light adjustable | No |
| Twilight setting TEACH | Yes |
| Constant-lighting control | No |
| Interconnection | Yes |
| Type of interconnection | Master/master |
| Interconnection via | Cable |

Accessories

| EAN 4007841 007638 | Remote control RC9 |
|--------------------|-----------------------------|
| EAN 4007841 608804 | Corner wall mount sensIQ S |
| EAN 4007841 608835 | Corner wall mount sensIQ S |
| EAN 4007841 009151 | Remote control Smart Remote |
| EAN 4007841 608828 | Corner wall mount sensIQ S |


Motion detector - Professional Line

sensIQ S


EVO black EAN 4007841 034979 Article number 034979



Detection Zone




Dimension Drawing




Mögliche Montagehöhe: 2,00 m – 5,00 m Orange: radial Schwarz: tangential 3 skallerbare Zonen


Light without neutral conductor



Connection using two-circuit switch for manual and automatic operation



Light with neutral conductor



Connection of 4-fold push-button coupler to DALI2 APC

